



Conventional Fire Alarm Manual Call Point RC-100

RC-100 is a manual call point for emergency and forced activation of the extinguishing process on the protected area.

The call point is designed to work with fire control panels, and it is suitable for surface indoor mounting that can be easily reset using its dedicated key, which is included with the product, and it does not require parts replacement after each activation. Additionally, this call point features an LED indicator, making it easily identifiable when activated.



Features

- Designed according to EN 54-11 standard.
- Compatible with the SENS conventional control panels
- SMD technology
- Reliable performance
- Low power consumption
- Impact-resistant plastic frame
- Equipped with a red LED status indicator.
- Easy reset with a dedicated key



Technical Specifications

Power supply voltage	27V
Stand by consumption	0
Alarm state current	25mA
Operating temperature	-10 to 70 °C
Humidity	95% (without condensation)
Type	Type A (For indoor use)
Dimensions	50×95×95 mm
Weight	130gr

Application

Considering the call point design, it is suitable for surface indoor mounting in stairwells and corridors.

Construction

The Sens fire alarm manual call point is made of ABS plastic and is designed in pieces that are easily assembled.